

METRAHIT | WORLD

International TRMS Multimeter

3-349-527-03
2/5.09

- Resolution: 100 μ V, 100 m Ω , 10 μ A, 10 pF, 0.1 Hz
- Precision temperature measurement (-50 ... +800 °C)
- Frequency and keying ratio measurement at 2 to 14 V signals up to 1 MHz
- Capacitance measurement
- RPM Measurement with Inductive Sensor (accessory)
- Automatic and manual measuring range selection
- Backlit digital display with additional analog scale
- Measured value memory, Hold, Max-Min value
- Overload and blown fuse indicators
- IP 40 protection
- Protective rubber holster
- 3 year guarantee
- DKD calibration certificate included as a standard feature



Quality Management System



DQS certified per
DIN EN ISO 900, reg. no. 1262



DKD
Calibration Certificate
DIN EN ISO/IEC 17025



Features

Automatic Blocking Sockets (ABS) *

Automatic blocking sockets prevent incorrect connection of measurement cables and inadvertent selection of the wrong measured quantity. This significantly reduces danger to the user, the instrument and the system under test, and eliminates it entirely in many cases.

Automatic / Manual Measuring Range Selection

Measured quantities are selected with the rotary switch. The measuring range is automatically matched to measured values. The measuring range can be selected manually as well with the help of the AUTO/MAN key.

Display of Negative Values at the Analog Scale

Negative values are also displayed at the analog scale for zero-frequency quantities, allowing for observation of measured quantity fluctuation around the zero-point.

Storage of Measured Values

By pressing the HOLD/ON key, the currently displayed measurement value can be „frozen“ in the display. The minimum and maximum values which were present at the input of the measuring instrument after activation of the MIN/MAX mode can be selectively "retained" with the MIN/ MAX function. The most important application is the determination of the minimum or maximum value during long-term observation of measurement quantities. MIN/MAX has no effect on the analog display; it continues to display the current measurement value.

Continuity Test

Allows for the detection of short-circuits and interrupted conductors. In addition to displaying test results, an acoustic signal can also be generated if desired.

Power Saving Circuit

The device is switched off automatically if the measured value remains unchanged for a period of approximately 10 minutes, and if none of the controls are activated during this time. Automatic shutdown can be deactivated.

Protective Cover for Harsh Conditions

The instrument is protected against damage in the event of impacts or dropping by means of a soft rubber cover with tilt stand. The rubber material also assures that the instrument does not wander if it is set up on a vibrating surface.

Keying Ratio Measurement – Measurement of 5 V Square-Wave Signals

This function makes it possible to test circuits and transmission cables by measuring the frequency and the keying ratio of pulses with amplitudes of 2 to 14 V and frequencies of 100 Hz to 10 kHz.

Voluntary Manufacturer's Guarantee

36 months for material and workmanship
1 ... 3 years for calibration (depending on application)

METRAHIT | WORLD

International TRMS Multimeter

Characteristic Values

Meas. Function	Measuring Range		Resolution 6000	Input Impedance == ~		Intrinsic Uncertainty at Max. Resolution under Reference Conditions		Overload Capacity		Meas. Function
						±(... % rdg. + ... d)	±(... % rdg. + ... d)	Value	Time	
V	600 mV		100 µV	>10 GΩ // < 40 pF	42 MΩ // < 50 pF	0.5 + 5	~	1000 V DC AC eff Sinus	Cont.	V
	6 V		1 mV	11 MΩ // < 40 pF	8 MΩ // < 50 pF	0.5 + 5				
	60 V		10 mV	10 MΩ // < 40 pF	8 MΩ // < 50 pF	0.5 + 5				
	600 V		100 mV	10 MΩ // < 40 pF	8 MΩ // < 50 pF	0.5 + 5				
	1000 V		1 V	10 MΩ // < 40 pF	8 MΩ // < 50 pF	0.5 + 5				
Voltage drop at approx. range limit						==	~			
A	60 mA		10 µA	100 mV	100 mV	1.0 + 5 (> 10 D)	1.5 + 5 (> 10 D)	1.0 A	Cont.	A
	600 mA		100 µA	700 mV	700 mV					
	6 A		1 mA	200 mV	200 mV					
	10 A		10 mA	300 mV	300 mV					
			Open-circuit voltage	Meas. current at range limit	±(... % rdg. + ... d)					
Ω	600 Ω		100 mΩ	max. 1 V	max. 250 µA	1 + 5 ²⁾	1000 V DC AC eff Sinus	max. 10 s		Ω
	6 kΩ		1 Ω	max. 1 V	max. 100 µA	0.7 + 3				
	60 kΩ		10 Ω	max. 1 V	max. 12 µA	0.7 + 3				
	600 kΩ		100 Ω	max. 1 V	max. 1,2 µA	0.7 + 3				
	6 MΩ		1 kΩ	max. 1 V	max. 120 nA	0.7 + 3				
	40 MΩ		10 kΩ	max. 1 V	max. 50 nA	2.0 + 3				
→	2 V		1 mV	max. 3 V		1.0 + 5				→
Ω)	600 Ω		0.1 Ω	max. 1 V	max. 250 µA	1.0 + 5				Ω)
						±(... % rdg. + ... d)				
°C	TYP K	-50,0 ... +400 °C	0,1 °C			1.0 + 5 ³⁾	1000 V DC/AC eff Sinus	max. 10 s		°C
		+401 ... +800 °C	0,1 °C			5.0 + 7 ³⁾				
°F	TYP K	-58 ... +752 °F	0,1 °F			1.0 + 9 ³⁾	1000 V DC/AC eff Sinus	max. 10 s		°F
		+753 ... +1472 °F	1 °F			5.0 + 11 ³⁾				
Power limit						±(... % rdg. + ... d)				
Hz (V ~)	100 Hz		0,1 Hz	3 x 10 ⁶ V x Hz @ U > 100 V		0.1 + 2	1000 V DC / AC			Hz (V ~)
	1000 Hz		1 Hz							
Hz	10 ... 100 Hz		0,1 Hz	3 x 10 ⁶ V x Hz @ U > 100 V		0.1 + 2	1000 V DC AC			Hz
	1000 Hz		1 Hz							
	1 MHz		1 Hz							
Power limit						±(... % rdg. + ... MR)				
%	30 Hz ... 1 kHz: 2,0 ... 98,0			3 x 10 ⁶ V x Hz @ U > 100 V		0.2% v.MUL + 8 D	1000 V	max. 10 s		%
	1 kHz ... 4 kHz: 5,0 ... 95,0									
	40 kHz ... 10 kHz: 10,0 ... 90,0									
Rpm	0.060 k... 99.99 k		1 Rpm	Discharge Resistance		± 2 Rpm	1000 V	max. 10 s		Rpm
F	40 nF		10 pF	10 MΩ		2.0 + 10 with zero activ	1000 D DC AC	max. 10 s		F
	400 nF		100 pF	1 MΩ		1.0 + 6				
	4 µF		1 nF	100 MΩ		1.0 + 6				
	40 µF		10 nF	12 MΩ		2.5 + 6				
	400 µF		100 nF	3 MΩ		5.0 + 6				

- 1) At 0 to + 40 °C
 2) With zero balancing, or + 35 digits without zero balancing
 3) Without sensor
 4) 12 A for 5 min, 16 A for 30 s

Key
 rdg. = reading (measured value)
 d = digit
 MUL = upper range limit
 MR = measuring range

METRAHIT | WORLD

International TRMS Multimeter

Influencing Quantities and Influence Error

Influencing Quantity	Sphere of Influence	Measured Quantity / Measuring Range	Influence Error ¹⁾ ±(... % rdg. + ... digits)
Temperature	0 °C ... +21 °C and +25 °C ... +40 °C	600 mV \equiv	1.0 + 3
		6 ... 600 V \equiv	0.15 + 1
		1000 V \equiv	0.2 + 1
		V \sim	0.4 + 2
		0 Ω ²⁾	0.15 + 2
		600 Ω ²⁾	0.25 + 2
		6 k Ω ... 6 M Ω	0.15 + 1
		40 M Ω	1.0 + 1
		mADC, ADC	0.5 + 1
		mAAC, AAC	0.75 + 1
		-50 ... +200 °C	0.5 K + 2
		+200 ... +400 °C	0.5 + 2
Measured Quantity Frequency	> 30 Hz ... 45 Hz	A \sim	2.0 + 10
	> 65 Hz ... 2 kHz	60 / 600 mA / 6 A	1.5 + 3
		10 A	2 + 10
	> 30 Hz ... 45 Hz	600 mV	3 + 10
		6 / 60 / 600 V	2.5 + 10
	> 65 Hz ... 500 Hz	1000 V	3.5 + 20
		600 mV	35 + 20
	> 65 Hz ... 2 kHz	6 / 60 V	2.5 + 10
		600 V	3 + 20
			1000 V

Influencing Quantity	Sphere of Influence	Measured Quantity / Measuring Range	Influence Error
Battery Voltage	\pm ³⁾ ... < 2.9 V > 3.1 V ... 3.6 V	V \equiv	± 2 Digits
		V \sim	± 4 Digits
		A \equiv	± 4 Digits
		A \sim	± 6 Digits
		60 Ω / 600 Ω / °C	± 4 Digits
		6 k Ω ... 40 M Ω	± 3 Digits
Relative Humidity	75% 3 days Instrument off	V \approx A \approx Ω °C	1 x intrinsic uncertainty
HOLD	—		± 1 Digits
MIN / MAX	—	V \approx , A \approx	± 2 Digits

¹⁾ For temperature: specified error valid starting with temperature changes as of 10 K.
For frequency: specified error valid starting with display values as of 300 digits.

²⁾ With zero balancing

³⁾ After the \pm symbol appears at the display

Influencing Quantity	Sphere of Influence	Measuring Ranges	Damping
Common Mode Interference Voltage	Interference quantity max. 600 V \sim	V \equiv	> 120 dB
		3 V \sim , 30 V \sim	> 80 dB
	Interference quantity max. 600 V \sim 50 Hz, 60 Hz sine	300 V \sim	> 70 dB
		600 V \sim	> 60 dB
Series Mode Interference Voltage	Interference quantity: V \sim , respective nominal value of the measuring range, max. 600 V \sim , 50 Hz, 60 Hz sine	V \equiv	> 50 dB
		Interference quantity max. 600 V \equiv	V \sim

Response Time (after manual range selection)

Measured Quantity / Measuring Range	Response Time		Measured Quantity Step Function
	Analog Display	Digital Display	
V \equiv , V \sim , A \equiv , A \sim	0.7 s	1.5 s	from 0 to 80% of the upper range limit
600 Ω ... 6 M Ω	1.5 s	2 s	from ∞ to 50% of the upper range limit
40 M Ω	4 s	5 s	
\rightarrow	— *	1.5 s	
\square)	— *	< 50 ms	
°C	— *	max. 3 s	from 0 to 50% of the upper range limit
F	— *	max. 5	

Reference Conditions

Ambient temperature + 23 °C ± 2 K

Relative humidity 40 ... 60%

Measured quantity frequency 45 ... 65 Hz

Measured quantity waveshape Sinusoidal

Battery voltage 3 V ± 0.1 V

Display

LCD panel (65 mm x 30 mm) with analog and digital display including unit of measure, type of current and various special functions

Analog:

Display LCD scale with pointer

Scale length 55 mm in all ranges

Scaling 0 ... ± 60 with 61 scale divisions in all ranges

Polarity display With automatic switching

Overflow display Triangle

Measuring rate 30 measurements per second

Digital:

Display / char. height 7-segment characters / 15 mm

Number of places $3^{6/7}$ -place \approx , 6000 steps

Overflow display „D.L.“ appears

Polarity display “-” sign is displayed if plus pole is connected to \perp

Measuring rate 3 measurements per second

Power Supply

Battery 2 x 1.5 V AA size batteries, alkaline manganese per IEC LR6 or equivalent rechargeable NiCd battery

Service life With alkaline manganese: approx. 750 hours for V \equiv , A \equiv
approx. 200 hours for V \sim , A \sim

Battery test \pm is displayed automatically if battery voltage drops to below approximately 2.1 V.

Electrical Safety

Safety class II per IEC 61010-1:2001/EN 61010-1:2001/
VDE 0411-1:2002

Measuring category 1000 V CAT III, 600 V CAT IV

Nominal voltage 1000 IV

Pollution degree 2

Test voltage 5.2 kV~ per IEC 61010-1/EN 61010-1

METRAHIT | WORLD

International TRMS Multimeter

Electromagnetic Compatibility (EMC)

Interference emission	EN 61326-1: 2006 class B
Interference immunity	EN 61326-1: 2006 EN 61326-2-1:2006

Fuses

Fuse links for all ranges up to 600 mA	FF 1.6 A/1000 V, 6.3 mm x 32 mm, switching capacity: 10 kA at 1000 V~ with ohmic load, protects all current measuring ranges up to 600 mA in combination with power diodes
--	--

Fuse links for all ranges up to 10 A	FF 10 A/1000 V, 10 mm x 38 mm, switching capacity: 30 kA at 1000 V with ohmic load, protects 6A and 10 A ranges to 1000 V
--------------------------------------	---

Data Interface

Type	Optical via infrared light through the housing
Data transmission	Serial, bidirectional (not IrDa compatible)
Protocol	Device specific
Baud rate	9600 baud

The USB plug-in interface adapter (see accessories) is used for adaptation to the PC's USB port.

Ambient Conditions

Accuracy range	0 °C ... + 40 °C
Operating temp.	-10 °C ... + 50 °C
Storage temperature	-25 °C ... + 70 °C without batteries
Relative humidity	45 ... 75%, no condensation allowed
Elevation	to 2000 m

Mechanical Design

Protection	IP 40, IP 20 at the connector jacks per DIN VDE 0470, part 1 / EN 60529
Dimensions	84 mm x 195 mm x 35 mm
Weight	Approx. 350 gr. with battery

Applicable Regulations and Standards

IEC 61010-1/EN 61010-1/ VDE 0411-1	Safety requirements for electrical equipment for measurement, control and laboratory use
EN 60529 VDE 0470, Part 1	Test instruments and test procedures Protection provided by enclosures (IP code)
DIN EN 61326-2-1 VDE 0843-02-2-1	Electrical equipment for measurement, control and laboratory use – EMC requirements – Part 2-1: Particular requirements for sensitive test and measurement equipment
DIN EN 60529 DIN VDE 0470 Part 1	Test Instruments and test procedures – Degree of protection provided by enclosures (IP code)

Standard Equipment

- 1 TRMS-digital multimeter
- 1 protective rubber holster
- 2 2 x 1.5 V AA size batteries
- 1 set of measurement cables KS17-2
- 1 DKD calibration certificate
- 1 short-form operating instructions

Detailed operating instructions are available on our website www.gossenmetrawatt.com.

Order Information

Description	Type	Article Number
Analog-digital multimeter with IR interface, standard equipment see above	METRAHIT WORLD	M206A
Accessories		
temperature sensor	TYP K	
Clip-on current transformer, 30 mA ... 150 A~, 1000:1, ±2.5 %, 1 mA/A	WZ12D	Z219D
Clip-on current sensor 60 / 600 A $\overline{\sim}$, 40 / 400 A \sim , 10 mV / A or 1 mV / A $\overline{\sim}$	Z13B	Z213B
Carrying pouch	F829	GTZ3301000R0003
Imitation leather carrying pouch for one METRAHit® and accessories	F836	GTZ3302000R0001
Imitation leather carrying pouch for two METRAHit®, adapter and accessories	F840	GTZ3302001R0001
Hard case for 1 METRAHit® and accessories	HC20	Z113A
Hard case for two METRAHit®, adapter and accessories	HC30	Z113B
Fuses (pack of 10)	FF 1.6 A / 1000 V	Z109C
Fuses (pack of 10)	FF 10 A / 1000 V	Z109L

For additional information on accessories, please refer to

- our „Measuring Instruments and Testers“ catalogue
- our website www.gossenmetrawatt.com